

Metal Halide Floodlights, 110V, 150W and 400W

The use of discharge fittings for site floodlighting has grown substantially in recent years with demand being driven by the need for low energy consumption, low fire risk and long lamp life. The big disadvantage of discharge floodlights has been that they are generally mains operated (230V) requiring the floodlight installation to be "permanent" i.e. fixed fittings fed via steel wire armoured cable, etc.

Blakley Electrics are pleased to introduce 150W and 400W metal halide floodlights suitable for operation at 110 volts. Fittings are rated at IP55, incorporate integral controlgear, a wall mounting bracket and are supplied complete with lamp. They can be installed using standard 1.5mm² PVC Arctic Grade yellow cable connected directly to a standard Reduced Low Voltage transformer. Fittings can be supplied loose (for the cable to be fitted on site) or they can be supplied pre-wired with an input lead complete with 16A 110V 3P plug for plugging into a Site Transformer or Extension Outlet Assembly.

Fittings can be wall mounted or mounted on a scaffold pole via the use of a half swivel clamp (see below for part numbers). Alternatively the fitting can be mounted on to the substantial PortaLite Tripod (see Data Sheet ref. HPDS16).

The 150W 110V Metal Halide floodlight is supplied in a black body and produces a light output of 13000 lumens, which is greater than a 500W tungsten halogen floodlight. In addition, due to the superior design of the reflector, there is a better dispersal of light and less glare.

The 400W 110V Metal Halide floodlight is supplied in a yellow body and produces a light output of 38000 lumens, making it a true wide area floodlight. It is also available with an integral photocell.

Part Numbers for 110V Floodlights and Accessories

Loose Floodlight, 150W c/w lamp	S060678
Floodlight 150W c/w lamp & 5M lead & plug	S060679
Spare Lamp, 150W	S120056
Loose Floodlight, 400W c/w lamp	S060699
Loose Floodlight, 400W c/w lamp and photocell	S060740
Floodlight 400W c/w lamp & 14M lead & plug	S060700
Spare Lamp, 400W	S120125
Scaffold Pole Clamp:	S060189
Scaffold Pole Fixings, M10	S060618
Tripod	PortaLite series



Loose Fitting, 400W - Part Number S060699



Loose Fitting, 150W - Part Number S060678



Pre-wired Fitting - Part Number S060679
(transformer supplied separately)

THE POWER PROFESSIONALS

HIGHER POWER **TRANS POWER** **SAFE POWER** **TEM POWER** **PRO POWER** **GREEN POWER**

• **SOUTH** 1 Thomas Road, Optima Park, Crayford, Kent DA1 4GA Tel: 0845 074 0084 Fax: 0845 074 0085

• **NORTH** Unit 55, Monckton Road Ind Estate, Wakefield WF2 7AL Tel: 0845 074 0086 Fax: 0845 074 0087

www.blakley.co.uk • sales@blakley.co.uk

THE COMPANY RESERVES THE RIGHT TO CHANGE PRODUCTS WITHOUT PRIOR NOTICE.



Cert. No. 902091

HPDS25 - 07/09